SMART LED FLASHER. MODEL FL-III



SMART LED FLASHER units can be connected with SMART INDUSTRIAL TELEPHONES, SMART LOUD HEARING PHONES, SMART LOUDRINGER it has an integrated annunciation system & can be connected directly to ANY SMART INDUSTRIAL TELEPHONE UNITS. Very useful in heavy, medium and small process industries.
When a call is made to the telephone, the FLASHER unit activates and flashing of the LED lamp is visible from a distance.

CONNECTIONS: -

1) Connect the FLASHER using single pair cable from the Industrial Telephone/Loud hearing Phone/Loud Ringer
2) Connect the power supply 220/110 VAC .

TECHNICAL SPECIFICATIONS: -

ELECTRICAL PERFORMANCE: -	
Visible range	100 Mtrs.
ELECTRICAL REQUIREMENTS: -	
Connection method	Plug in type.
Fuse	1 Amp 2AG fast blows.
Power supply	220/110 VAC.
ENVIRONMENTAL: -	
Temperature	0 to +60 C.
Humidity	0 to 95% Rh non-condensing.
Enclosure	IP 65 Dustproof fully gasketted.
MECHANICAL: -	
Body	ABS.
Surface finish	Powder coated.
Dimensions of ABS box	140 x 120 x 100 mm.
Net weight kgs	0.8 kg.
Standard mounting	Vertical/horizontal wall.

CONFIRMING TO IP65/NEMA-4 DEGREE PROTECTION.

I N D U S T R I A L C O M M U N I C A T I O N S S I M P L I F I E D .

Cables & Wireless Co.

FF 75 RAJAT ARCADE, MIDC T-POINT,
AMRAWATI ROAD, WADI,
NAGPUR –440023.MAHARASHTRA ,INDIA.
PHONE:-+917104-321913, +917104-224381
FAX:- +917104-224381.
Cell: - +9198226 95746, +919145610269, +919822941190.
Website:- www.cnwcom.in.E-mail: - cnwcom@gmail.com.

"(Specifications and description subjected to change without prior notice)"